

1,500 VDC Combiner

Options:

- *Load Break Disconnect
- *Custom Versions
- *4 up to 36 Strings
- *NEMA Type: 3R/4/4X Enclosures
- *Dual Output lugs
- *Grounded or Ungrounded configurations
- *Rated up to 400 Amps
- *Surge Protection Device

Disconnect Ampacity	275 Amps	325 Amps	400 Amps
Number of Circuits	18	28	36
Input Wire Size	14 - 8 AWG	14 - 8 AWG	14 - 8 AWG
Max Fuse Size:	30 Amps	30 Amps	30 Amps
Number of Outputs	1 or 2	1 or 2	1 or 2
Output Wire Size:	6 - 350 Kcmil	2 - 600 Kcmil	2 - 600 Kcmil
Metal Enclosure type 3R/4	24x24x8	30x24x8	30x30x8
Type 4X Enclosure	24x24x8	30x24x8	36x30x8